

# HDMI Audio Extractor 4K 30 Hz compact

## Description

This adapter by Delock can be used to extract the audio signal from an HDMI transmission. While the video signal is displayed on a TV or monitor, the audio signal can be sent digital (S/PDIF) or analogue (stereo) to other devices, such as headphones or a surround receiver.



**Item no. 62784**

EAN: 4043619627844

Country of origin: China

Package: Retail Box

## Technical details

- Connectors:
  - Input:
    - 1 x HDMI-A 19 pin male
    - 1 x USB Type Micro-B female (5 V power supply)
  - Output:
    - 1 x HDMI-A 19 pin female
    - 1 x 3.5 mm 3 pin stereo jack female (audio)
    - 1 x TOSLINK female S/PDIF
- High Speed HDMI, 3D and HDCP 1.4
- Automatic switching to stereo (2.0) when using the stereo jack and automatic muting of the digital output
- Resolution up to 3840 x 2160 @ 30 Hz (8 bit), 1920 x 1080 @ 60 Hz (12 bit)
- Video bandwidth up to 300 MHz / 3 Gb/s per channel, 9 Gb/s max.
- Supports all common 2.0 and 5.1 audio formats: LPCM, Dolby Digital, DTS Audio
- Supported sample rates: 16 / 20 / 24 bit, 32 / 44.1 / 48 / 88.2 / 96 kHz (depending on the system and the connected devices)
- HDMI audio routed to the output (pass-through)
- Power consumption: max. 2 W


## System requirements

- A free HDMI-A female
- A free USB Type-A female port

## Package content

- HDMI Audio Extractor
- USB Type-A to Type Micro-B cable, length ca. 15 cm
- User manual

## Images



## General

Specification:	DTS Audio Dolby Digital HDCP 1.4 HDMI 1.4 LPCM
----------------	--

## Interface

Output:	1 x 3.5 mm 3 pin stereo jack female 1 x TOSLINK female 1 x HDMI-A female
Input:	1 x USB 2.0 Type Micro-B female 1 x HDMI-A male

## Technical characteristics

Maximum screen resolution:	3840 x 2160 @ 30 Hz
Video bandwidth:	300 MHz

## Physical characteristics

Housing colour:	black
Housing material:	Plastic

## Manufacturer information

Street	Beeskowdamm 13/15
Postal code	14167
City	Berlin
Country	Deutschland
E-Mail	info@delock.de
Website	www.delock.de